



VIPERLINK USA
strike with clarity

VPL-900 THE RATTLER

HIDDEN FEATURES - OPERATOR SHORTCUTS

Your radio includes several advanced shortcuts designed to make operation faster and more efficient. These features allow experienced operators to quickly access scanning, channel storage, bank switching, and group selection without navigating through menus.

-SAVE A VFO FREQUENCY TO A CHANNEL

You can store a manually entered frequency into a channel memory location.

•Steps•

1. Press and hold the * (star key)
2. Enter the desired channel number
3. Press the * key again to save

The current VFO frequency will now be stored to that channel.

-START CHANNEL SCANNING-

The radio can automatically scan programmed channels for activity.

To start scanning:

Press and hold 1 for 2–3 seconds.

The radio will begin scanning available channels.

-SWITCH BETWEEN VFO MODE AND CHANNEL MODE-

Your radio supports two operating modes.

•VFO Mode•

Manually tune frequencies.

•Channel Mode•

Access stored channels.

To toggle between modes

Press the # key.

-SWITCH BETWEEN POC AND ANALOG BANKS-

Your radio separates PoC and Analog functions into different banks.

•To switch banks•

Press the * key briefly.

The green selection arrow will move between the PoC bank and the Analog bank.

-DELETE A STORED CHANNEL-

If you need to remove a saved channel:

(Ensure the radio is in Channel Mode)

Press and hold 3 for 2–3 seconds

The Delete Channel prompt will appear

Confirm the deletion

-QUICK CALL FEATURE-

Quick Call allows operators to instantly jump to commonly used groups.

•Steps•

1. Assign a Quick Call Group
 2. Open the Group List
 3. Select the desired group
 4. Choose Quick Call instead of Enter Group
 5. Assign the group to a number 1–9
- (Up to 9 groups can be assigned for Quick Call access.)

•Use Quick Call•

1. Press and hold the P1 (button located below the green button)
 2. Press the Quick Call number (1–9)
- (The radio will immediately switch to that group.)

OPERATOR SHORTCUT REFERENCE

- Start Scan** = Hold 1 for 2-3 seconds
- Save VFO to Channel** = Hold *, enter channel number, press * again
- Switch VFO / Channel Mode** = Press #
- Switch PoC / Analog Bank** = Short press *
- Delete Channel** = Hold 3
- Quick Call Group** = Press and hold P1, then press 1–9 to select