## **HYUNDAI**

## hyundaipowerequipment.co.uk





Please note: Product might be different from pictures shown. Specifications might vary due to continuous product development.

## HY10000LEK-2 8kW / 10.0kVA Recoil / Electric Start Site Petrol Generator

- Ideal for site use, commercial use, tradesmen or simply home / garage use.
- Powerful Hyundai 459cc / 16hp 4-Stroke engine coupled with a superior quality Hyundai AVR alternator.
- The AVR (Automatic Voltage Regulator) keeps the output stable, within +/- 3% of 230V. This ensures it is suitable to power sensitive equipment.
- Electric push button, ensuring easy power when you need it.
- Improved muffler design including a spark arrestor. This reduces noise levels and makes the unit more environmentally friendly compared to traditionally designed models.
- Low oil alert shuts down the engine automatically if the oil level drops, this prevents irreversible damage to the engine.
- Built in circuit breaker which cuts off power when overloaded.•

Easily portable thanks to the integrated wheel kit.

\*kVA is based on an assumed load factor of 0.8.

## **Specifications**

**MODEL** 

**MAX OUTPUT** 

**ENGINE** 

DISPLACEMENT ENGINE SPEED

**FUEL TANK CAPACITY** 

**FUEL TYPE** 

**OIL TYPE** 

OIL TANK CAPACITY

**BATTERY SIZE** 

START METHOD

**FREQUENCY** 

**VOLTAGES** 

RUN TIME ½ LOAD

SOUNDE LEVEL

**OUTLET SOCKETS** 

**NET WEIGHT** 

HY10000LEK-2

8.5kW

16hp

459cc

3000rpm

25L

Unleaded

**SAE15W40** 

1100ml

12V

Recoil / Electric

50Hz

230V

12.5hrs

2 x 16A 230V, 1 x 32A 230V

96dB(A)

94kg

