





Please note: Product might be different from pictures shown. Specifications might vary due to continuous product development.

HY1000Si Petrol Inverter Generator

- 1.6hp 4 stroke petrol engine with low oil protection.
- Produces a maximum output of 1kW (1000w).
- Compact and lightweight design weighing 14kg.
- Low sound levels, just 58dB @ 7m.
- 2.2L fuel tank which provides a maximum runtime of 6.6hrs.
- ECO mode for low fuel consumption.
- Full LED display for quick and easy performance monitoring.
- Pure sine wave output for powering sensitive electronic appliances.
- 1 x 230v / 12v DC socket.

Specifications

HY1000si

MODEL **ENGINE MODEL ENGINE TYPE ENGINE SIZE OIL CAPCITY** FUEL **NOISE LEVEL RATED SPEED RATED POWER MAX POWER START METHOD FUEL TANK CAPACITY APPROX RUN TIME PER TANK** VOLTAGE FREQUENCY SOCKET TYPE SOCKET TYPE ALTERNATOR VOLTAGE REGULATION CASING **BOX DIMENSIONS L x W x H GROSS WEIGHT** FULLY ASSEMBLED DIMENSIONS L x W x H **DRY WEIGHT**

HX53 (XG - 144F) **OHV - Single Cylinder - 4 Stroke** 53cc 250ml **Unleaded Petrol** 90/58dB (A) @ 7m 5500rpm 0.9kW 1kW Recoil 2.2L 3.3hr @ 50% load **230VAC** 50Hz 1 x 230 VAC / 3.9A 12 VDC / 5A **Solid State Regulator** Plastic 490mm x 280mm x 405mm 17kg 451mm x 242mm x 379mm 14kg



T: 01646 687 880 E: info@hyundaipowerequipment.co.uk