

POWERCENTER 15 GENERATOR

ALTERNATOR

| | | | |
|-----------------|---------------|-------|-----------|
| Three Phase | Rated Output | (kVA) | 15 |
| | Rated Voltage | (V) | 415 |
| | Rated Current | (A) | 20.9 |
| | Power Factor | | 0.8 |
| Single Phase | Rated Output | (kVA) | 15/12 |
| | Rated Voltage | (V) | 240/110 |
| | Rated Current | (A) | 50/109.1 |
| | Power Factor | | 1.0 |
| Rated Frequency | | (Hz) | 50 |
| Excitation | | | Brushless |
| Number of Poles | | | 2 |

- Fully bundled
- Multi-voltage
- Super silent
- Compact design

ENGINE

| | | |
|--------------------|----------|--------|
| Model | (Kubota) | D902 |
| Rated Speed | (min-1) | 3000 |
| Fuel | | Diesel |
| Fuel Tank Capacity | (L) | 37 |
| Fuel Consumption | (L/Hr) | 3.5 |
| Lubricant Capacity | (L) | 3.6 |
| Coolant Capacity | (L) | 4.0 |

SET

| | | |
|-----------------|--------------------------|----------------------------|
| Dry Weight | (kg) | 390 |
| Length | (mm) | 1,410 |
| Width | (mm) | 635 |
| Height | (mm) | 780 |
| Noise | (dB*A/7m) | 63.5 |
| | (LWA*dB) | 91.5 |
| Bunded | | YES |
| Emergency Stop | | YES |
| Digital Display | | YES |
| Outputs | Three Phase | (415V) 1 x 32Amp |
| | Single Phase | (240V) 2 x 32Amp 1 x 16Amp |
| | Single Phase | (110V) 2 x 32Amp 1 x 16Amp |
| | Hard Wire/Terminal Board | YES |

