



**SIGNETMARINE** INC.

291 West 22nd Street Unit 104  
San Pedro, CA 90731  
signetmarine.com

# MK30 Wiring Diagram

NOTE:

Wire colors correlate to the current SignetMarine wire. Older wire (+12 years) had a few different colors as noted below.


OLD WIRE: = NEW WIRE:

RED	RED
WHITE	WHITE
PURPLE	SHIELD/BARE
ORANGE	ORANGE
YELLOW	BROWN
BLACK	BLACK
GREEN	GREEN
BLUE	BLUE

MASTHEAD WIRE (8 WIRES)




TO MASTHEAD ↑

1. Black
2. Red
3. Bare Wire/Shield
4. Not Used
5. Not Used
6. Not Used
7. Not Used
8. Not Used



(The side of the connector the pins are connected to.)

W/S = WINDSPEED  
W/D = WIND DIRECTION



NOTE:  
Resistance between yellow, or brown wire and blue wire is 4000 OHMs (+- 10%) when cups not spinning.



The Red wire on the MK30 connects to the blue wire coming down from the mast.  
The Black wire on the MK30 connects to the yellow or brown wire coming down from the mast.  
The bare wire on the MK30 connects to violet or bare.