



PATRIOT[®] VOICE EZ

Advanced Easy to Use Reading Appliance

User Manual

1-800-364-1608



Congratulations on your purchase of the Patriot VOICE EZ.

Hear your mail, newspapers, books, magazines, and much more read out loud.

Please take a moment to acquaint yourself with the three easy to use knobs on the unit that allow you to set the preference to best meet your needs.

Enclosed in package is the Patriot VOICE EZ portable reader, the AC adapter, and this User Manual.

We again thank you and are pleased you are empowered with this adaptive device to maintain your quality of life and independence.

Instructions on Use

Step One - Remove unit from box and set the unit atop a sturdy surface upright with handle on top and the three control knobs facing the user. We suggest you take a moment to gently feel the entire unit from top handle to the rear of the unit and canvas your hands over the sides, the bottom, and the canopy that houses the three tactile controls.

Step Two - Connect the power adapter to a standard household 110V outlet, then plug the opposite end into the inlet located in the rear of the unit.

Step Three - Locate the power switch on the back of the machine. Press the switch to turn on the machine, the audible sound signifies power has successfully been turned on. There will be a series of ticktocks for about 20 seconds which is then followed up by an audio announcement "Please put the document on the reading surface". At this moment it is ready to operate!

Instruction for Use - Continued

Step Four - Place your document onto the base, aligning the document with the edges of the base. Remove your hands out of the way so there is a clear unobstructed view of the document.

Please Note: Direction of document is irrelevant as the unit can read in a full 360 degree pattern, sideways, upside down and vice versa. The document does need to be face up.

Step Five - The unit will begin reading aloud automatically.

**Turn for Speed
& Press for
Scan**



**Turn for REW/FWD & Press
to Pause or Resume**

**Turn for Volume &
Press for Spelling**

Instruction for Use - Continued

Step Six - The controls are as follows:



Left knob - allows you to take a picture of your document to read aloud by pressing the knob in. This is especially useful when reading a book by allowing you to simply turn the page and then push this knob in to have the next page read out loud. Turning this left knob will change the reading speed. Turning counterclockwise will decrease the reading speed and turning clockwise will increase the reading speed.



Center knob - Press in the middle knob to pause or resume reading. You can turn the same middle knob in the clockwise direction to advance forward reading and turn the knob in the counter clockwise direction to rewind.



Right knob - Press in the right knob to hear the spelling of the current word that it is reading out loud. Turn the right knob to increase or decrease the volume.

Note: When changing speed, volume, or when rewinding or fast forwarding, the Patriot will be paused afterwards. You will need to push in the middle knob to resume reading.

Pressing in the two left knobs at the same time will change the voice of the spoken content. There are two english voices and two spanish voices. The two english voices will only read english print and the two spanish voices will only read spanish print. The Patriot does not translate or read handwriting.

Pressing in the two right knobs at the same time will change the Patriot to document mode or table mode. The document mode is the preset default mode. It would be the proper setting to use to read down one column of text and then go to the next, such as how to properly read a newspaper. Table mode is better for reading financial statements. For example, you would hear "ATM deposit", and then hear the dollar amount. Instead of hearing all of the places of transaction occurrences and then hearing all of the dollar amounts, which is how the default document mode would read, and not always ideal.

Patriot Voice EZ Side View



AUX: The AUX port is for headphones. The Patriot Voice EZ can use any 3.5mm wired headphones.

USB: The USB port will allow you to store images taken by the Patriot Voice EZ directly on your USB drive (not included). Once you insert the USB thumb drive into the Patriot Voice EZ, you will hear the device say "USB key inserted". Now the Patriot Voice EZ is in book mode. This mode will allow you to take multiple pictures of your document with out the device reading it out loud. Once you are done taking pictures, push the pause/ play (middle knob) in. The Patriot Voice EZ will now convert your images into 3 different formats. the formats are as follows:

- 1- .JPEG: a image file**
- 2- .TXT: a text file**
- 3- .MP3: a audio file**

**The Patriot Voice EZ will let you know when the converting is complete.
Times may vary due to home many images it is
converting.**

The thumb drive can be accessed via a computer now.

Register Your Patriot® Device for an Extended 3-Year Warranty!

By registering your new Patriot® device **within 3 months of purchase**, you will receive an extended warranty for a total of 3 years. Take advantage of this added peace of mind by following one of the simple registration methods below:

To register your new Patriot® device, please use a mobile device to scan the QR code. This will bring you to our website to register.



Inside of the packaging, you will also find a Product Registration Card. Please fill out this card completely and mail it back to us at:

2125 SW Highway 484
Ocala, FL 34473

If you do not own a mobile device or are unable to mail the registration card, please call us at 1-800-364-1608 to register your device over the phone.

Patriot VOICE EZ Specifications

Power: 12V DC 3.0A

Dimension without Packaging : 14"H x 11"W x 9"D

Weight without Packaging : 6 LBS.

**Dimension with Packaging : 16"H x 13"W x 11"D Weight
with Packaging : 12 LBS.**

Camera: Fixed Focus

Lighting : USB LED

Constant Scan Software: Proprietary Interface

Body: 4mm Thick Aluminum Powder Coated White

Warranty: Two Years Standard Parts and Labor

Headphone Jack: 3.5 mm (left side of machine)

USB Jack: Type A USB (left side of machine)



For question or support, please contact us at:

800-364-1608 / 352-203-4164

Fax: 352-203-4617

Website: www.patriotvision.com

Email: info@patriotvision.com

Support Email: support@patriotvision.com

Patriot Vision Industries, LLC, is an affiliate of Low VisionAids, Inc. Patriot, Magnifying America, the words and their symbols/logo/mark are licensed trademarks owned by Low VisionAids, Inc.

Copyright 2026. All Right Reserved. Designed & Assembled in USA.

Please be advised that this user guide may contain errors, and is therefore subject to being changed or updated without prior notice.